

HƯỚNG DẪN SỬ DỤNG

Tai nghe Bluetooth Q6C


Công nghệ không dây

Với công nghệ không dây, bạn có thể dễ dàng kết nối tai nghe với các thiết bị khác mà không cần dùng đến dây cáp. Công nghệ không dây hỗ trợ kết nối trong khoảng cách ngắn (làm việc bình thường trong một khoảng cách 10M) giữa các thiết bị số như điện thoại di động/ tai nghe không dây/ máy tính... Công nghệ Bluetooth hiệu quả và đơn giản hóa cách liên lạc, làm cho thiết bị truyền dữ liệu ra một cách nhanh chóng và hiệu quả. Trong một số khu vực, có thể có một số hạn chế khi sử dụng công nghệ không dây bluetooth. Hãy tham khảo ý kiến thẩm quyền hoặc địa phương của bạn để biết thêm chi tiết.

1

Vị trí điều khiển

1. MFB (phím đa chức năng)
2. Đèn LED
3. Micro
4. Cổng sạc micro USB
5. Ống loa
6. Móc tai



2

Sạc đầy tai nghe trước khi sử dụng. Để biết chi tiết về cách sạc tai nghe, xem phần "Bộ sạc và pin" trong hướng dẫn sử dụng này. Chọn điện thoại di động tương thích với tai nghe hoặc các thiết bị Bluetooth khác để ghép nối với tai nghe. Để biết chi tiết về cách kết nối, xem phần "Hoạt động cơ bản".

Lưu ý: Giữ tai nghe cách xa thẻ tín dụng của bạn hoặc thiết bị từ tính khác; Nếu không, thông tin được lưu trữ có thể bị mất.

Các tính năng và chức năng của sản phẩm:

- Tai nghe Bluetooth siêu nhỏ, gọn nhẹ
- Móc tai có thể điều chỉnh, ổn định và thoải mái khi đeo
- Kết nối ổn định, tín hiệu cuộc gọi rõ ràng
- Hạn chế bám bẩn & trầy xước

Cách kết nối với tai nghe Bluetooth (Lưu ý: ví dụ điện thoại Iphone)

1. Nhấn và giữ phím đa chức năng khoảng 3 giây đến khi đèn báo màu đỏ và xanh nhấp nháy. Khi vào chế độ

3

sẵn sàng kết nối, đèn sáng nhấp nháy luân phiên.

2. Bật chế độ Bluetooth trên điện thoại.

3. Tìm tai nghe Bluetooth “Q6C” để kết nối.

Hoạt động cơ bản

Bật nguồn: Nhấn và giữ phím đa chức năng khoảng 3 giây, đèn báo màu đỏ và xanh nhấp nháy cùng lúc, âm báo " Power On, Pairing" được phát ra trên tai nghe, sau đó tự động chuyển sang chế độ ghép nối với đèn đỏ và xanh nhấp nháy luân phiên. Tai nghe sẽ tự động tắt nếu việc kết nối không hoàn thành trong vòng 150 giây.

4

Kết nối: Sau khi kết nối thành công với điện thoại, âm báo " Pairing Success,sound Connected " được phát ra. Nếu phiên bản Bluetooth của tai nghe thấp hơn V2.1, bạn cần nhập mật khẩu "0000".

Tự động tái kết nối: Khi bật nguồn, tai nghe được tự động kết nối với điện thoại di động mà tai nghe đã được ghép nối trước đó.

Cúp máy: nhấn vào phím đa chức năng khi đang trong cuộc gọi.

Từ chối các cuộc gọi đến: Khi có cuộc gọi đến, nhấn và giữ phím đa chức năng đến khi phát tiếng bíp.

Chuyển đổi âm thanh cuộc gọi: trong lúc thực hiện cuộc gọi, nhấn 2 lần vào phím đa chức năng để chuyển âm thanh sang điện thoại. Lặp lại hành động này để

5

chuyển trở lại tai nghe.

Trả lời cuộc gọi: Khi có cuộc gọi đến, tai nghe sẽ tự động đọc số điện thoại đến. Bấm 1 lần vào phím đa chức năng để trả lời cuộc gọi.

Quay lại số được gọi cuối cùng: Ở trạng thái chờ sau khi đã kết nối, nhấn và giữ phím đa chức năng trong khoảng một giây rồi thả ra, sẽ có âm báo “Redial”. Nhấn vào phím đa chức năng một lần nữa để hủy gọi lại.

Phát / tạm dừng nhạc: Nhấn 1 lần phím đa chức năng để phát nhạc. Nhấn thêm lần nữa để tạm dừng nhạc.

Khôi phục cài đặt gốc: Ở trạng thái đang sạc, nhấn giữ phím đa chức năng khoảng 9 giây cho đến khi tắt chức năng để khôi phục cài đặt gốc.

6

Tắt nguồn: Nhấn và giữ phím đa chức năng khoảng 3 giây ở bất kỳ trạng thái nào, đèn màu đỏ và màu xanh nhấp nháy cùng lúc ba lần và bạn sẽ nghe thấy âm báo “Power Off”.

Bắt đầu / Tắt điều khiển giọng nói: Ở trạng thái chờ sau khi kết nối, nhấn 2 lần vào phím đa chức năng đến khi nghe thấy tiếng bíp. Nhấp 2 lần vào phím đa chức năng lần nữa để hủy điều khiển giọng nói (Điện thoại di động phải hỗ trợ điều khiển giọng nói).

Chức năng đa điểm:

1) Kết nối tai nghe Bluetooth với điện thoại di động A, và sau đó tắt chức năng Bluetooth của điện thoại di động A. 2) Kết nối tai nghe Bluetooth với điện thoại di động B.

7

3) Mở chức năng Bluetooth của điện thoại di động A, sau đó tai nghe sẽ tự động kết nối với điện thoại di động A (điện thoại di động cần có chức năng tự động kết nối); hoặc bấm vào điện thoại di động A để tự kết nối thủ công. Bây giờ, tai nghe Bluetooth đã kết nối với điện thoại di động A và B, chức năng đa điểm của một tai nghe Bluetooth là kết nối được hai điện thoại di động cùng lúc.

Cuộc gọi ba bên: 1) Khi có cuộc gọi mới trong khi đang trao đổi cuộc gọi, nhấn vào phím đa chức năng để kết thúc cuộc gọi hiện tại và trả lời cuộc gọi mới (một vài điện thoại cần phải bấm phím đa chức năng lần nữa). 2) Nhấn và giữ phím đa chức năng khoảng một giây để

8

giữ cuộc gọi hiện tại (Gọi A) và trả lời Cuộc gọi B. Nhấn và giữ lại phím đa chức năng khoảng một giây nữa để chuyển sang Gọi A. Lặp lại hành động này để chuyển cuộc gọi A / B. 3) Nhấn vào phím đa chức năng một lần trong lúc trao đổi cuộc gọi để kết thúc cuộc gọi hiện tại và thực hiện cuộc gọi khác.

Sạc và pin

Trước khi sử dụng bất kỳ bộ sạc nào để sạc tai nghe này, hãy kiểm tra xem các thông số kỹ thuật của bộ sạc có đáp ứng yêu cầu hay không. Điện áp đầu ra của bộ sạc nên là DC5V +/- 0.25V và dòng điện đầu ra nên là 100 mA đến 500 mA. Điện áp sạc quá cao có thể làm hỏng tai nghe.

9

Cảnh báo: Sử dụng bộ sạc được gợi ý bất cứ khi nào có thể. Việc sử dụng các loại bộ sạc khác có thể vi phạm các điều khoản bảo hành của thiết bị và dẫn đến nguy hiểm. Nếu cáp sạc đi kèm với tai nghe, hãy kết nối cáp với bộ sạc hoặc máy tính đã được chứng nhận CCC để sạc tai nghe.

Sạc pin

Tai nghe sử dụng pin không thể tháo rời. Không tìm cách tháo pin ra khỏi tai nghe; nếu không, tai nghe có thể bị hỏng. Nếu tai nghe không được sử dụng trong một thời gian dài, hãy giữ nó ở nơi khô ráo, thoáng mát, sạc tai nghe ít nhất hai tháng một lần.

10

1. Nếu nghe thấy âm báo “Please Charging”, pin tai nghe bị yếu, cần phải sạc tai nghe bằng cách kết nối cáp của bộ sạc vào cổng sạc trên tai nghe.
2. Kết nối bộ sạc với ổ cắm điện.
3. Đèn báo màu đỏ khi tai nghe được sạc. Nếu chưa được sạc, hãy tháo tai nghe khỏi ổ cắm điện và lắp lại tai nghe một lần nữa. Thời gian sạc khoảng 2 giờ. Đèn chuyển sang màu xanh khi pin được sạc đầy.
4. Pin được sạc đầy có thể sử dụng được khoảng 4 giờ đàm thoại hoặc thời gian chờ 70 giờ. Thời gian đàm thoại và thời gian chờ thực tế có thể thay đổi tùy theo điện thoại di động, cài đặt, phương pháp sử dụng và môi trường xung quanh.

11

Xử lý sự cố

Sự cố	Nguyên nhân	Giải pháp
Tai nghe không thể bật lên nguồn	Hết pin	Sử dụng bộ sạc để sạc đầy pin.
	Nút nguồn không được nhấn và giữ đủ thời gian.	Nhấn và giữ nút nguồn một lần nữa.
Tai nghe không thể sạc được.	Cổng sạc không được kết nối đúng cách.	Kết nối lại cổng sạc.
Tai nghe không thể tắt nguồn.	Chương trình tai nghe bị lỗi do hoạt động không đúng cách.	Sử dụng bộ sạc để sạc và cài đặt lại tai nghe.
Tai nghe không thể tìm kiếm được hoặc kết nối thất bại.	Tai nghe không vào trạng thái kết nối.	Cho phép tai nghe vào trạng thái ghép nối.
	Ứng dụng Bluetooth của điện thoại di động không ổn định.	Tắt nguồn và sau đó vào lại điện thoại di động để kết nối điện thoại với tai nghe.

12

Lưu ý:

1. Để kéo dài tuổi thọ của pin, bạn nên sạc tai nghe ít nhất mỗi tháng một lần.
2. Vui lòng sử dụng bộ sạc kèm theo hoặc các bộ sạc có nguồn gốc rõ ràng để sạc tai nghe
3. Điều chỉnh âm lượng thích hợp khi sử dụng tai nghe.
4. KHÔNG đeo tai nghe khi đang ngủ; nếu không, tai nghe có thể bị hỏng
5. Giữ tai nghe xa tầm tay trẻ em. Các thành phần nhỏ của tai nghe có thể gây nguy hiểm cho trẻ.

13

Welcome

Thank you for choosing our products. The company Bluetooth earphonehas a fashionable design, powerful functions, and high compatibility, providing you with hands-free convenience in making calls and listening to music. It is your best choice in office and during traveling and driving.

Bluetooth Wireless Technology

With the Bluetooth wireless technology, you can connect the headset to its compatible communication devices without using cables. The Bluetooth wireless connection allows you to use a cell phone without holding it against the headset, but the maximum distance between them

14

played. If the Bluetooth version of the headset is earlier than V2.1, you need to enter the pairing password "0000".

Automatic Re-Connecting: When powered on, the earphone is automatically connected with the cell phone that the earphone has previously paired with. Hang up calls: During call communication, click MFB button with a beep.

Reject incoming calls: When a call is coming, long press MFB button for 1 second with a beep.

Audio line switch of call: During call communication, double click MFB button to switch the audio line to cell phone. Repeat this action to switch back to earphone.

19

Charging the Battery


The earphone use embedded charging battery that cannot be removed. Do not attempt to remove the battery from the earphone; otherwise, the earphone may be damaged. If the earphone is not used in a long time, keep it in a cool and well-ventilated place, and charge the earphone once every two months. 1. If a prompt tone“Please Charging”is heard, the earphone battery is low. If the earphone continues to work, it may be automatically powered off. At this time, you need to charge the earphone by connecting the cable of the charger to the charging port on the earphone.

24

cannot exceed 10 meters (about 30 inches). The Bluetooth wireless connection may be interfered by obstacles (such as walls) or other electronic devices. In some areas, use of the Bluetooth wireless technology may be subject to some constraints. Please consult your local authority or service provider for details.

Location of controls

- 1. MFB (Multi Function Button)
- 2. LED indicator
- 3. Microphone
- 4. Micro USB charging port
- 5.Megaphone
- 6. Ear hook



15

Call answer: When a call is incoming, it will auto read incoming phone number. Click MFB button once to answer the call.

Re-dial the last called number: Under standby status after connection, long press MFB button for about one second then release, there will be a voice of “Redial”. Click MFB button once again to cancel number re-dial.

Music play / pause: Click MFB button once to play music. Repeat the action to pause music.

Restore factory settings: At charging status, long press MFB about 9 seconds until the indictors are off to restore the factory settings.

20

- 2. Connect the charger to an AC power socket.
- 3. The red indicator is on when the earphone is being charged. If the charging is not started yet, disconnect the earphone from the power socket, and reconnect the earphone again. It takes about 2 hours to fully charge the earphone. After battery charging is completed, the red indictor is off, and the blue indicator is on. At this time, you can the charger from the power socket and earphone.
- 4. A fully charged battery can provide about 4hours of talk time, or 70hours of standby time.The actual talk time and standby time may vary with cell phones, settings, use methods, and environment.

25

Fully charge the earphone before using. For details about how to charge the earphone, see "Charger and Battery" in this manual. Meanwhile, choose the cell phone that is compatible with the earphone or other Bluetooth devices to pair with the earphone. For details about pairing, see "Basic Operations".

Tip: Keep the earphone away from your credit card or other magnetic storage media; otherwise, the stored information may be lost due to demagnetization.

Product features and functions:

- Super mini Bluetooth earphone, small and light
- Adjustable ear hook with skin-friendly material, stable and comfortable for wearing

16

Power off: Long press MFB about 3seconds at any status, the red and blue indicators blink at the same time for three times, and you will hear a voice of “Power Off”.

Start / Shut the voice control: At standby status after connection, double click MFB button, you will hear a sound of a beep. Double click MFB button again to cancel the voice control (Cell phone must support voice control).

Multi-point function:

1)Connect the Bluetooth earphone with cell phone A, and then close Bluetooth function of cell phone A. 2) Connect the Bluetooth earphone with cell phone B. 3) Open Bluetooth function of cell phone A, then the earphone will auto connect cell phone A (cell phone needs to have auto

21

Troubleshooting		
Problem Description	Cause	Solution
The earphone cannot be powered on	The battery is exhausted.	Use the charger to fully charge the battery.
	The power button is not pressed and held for sufficient time.	Press and hold the power button again.
The earphone cannot be charged.	The charging port is not properly connected.	Reconnect the charging port.
The earphone cannot be powered off.	The earphone program is in error due to an incorrect operation.	Use the charger to charge and reset the earphone.
The earphone cannot be searched or pairing fails.	The earphone does not enter the pairing state.	Enable the earphone to enter the pairing state.
	The Bluetooth application of the cell phone is in error.	Power off and then on the cell phone to pair the cell phone with the earphone.

26

- Super clear communication design, clear call communication
- Multi-layer technological protection, prevent dirty and scratch

How to connect with the Bluetooth earphone (Note: Use iPhone for example)

1.Long press MFB about 3seconds, the red and blue indicators blink at the same time for three times, then auto enter into a pairing mode with red and blue light flash alternately

2. Open the Bluetooth software of your phone, searching

17

connect function); or click cell phone A for manual connection. Now the Bluetooth earphone has already connected cell phone A and B, realizing the multi-point function of one Bluetooth earphone connects two cell phones.

Three-party calling: 1) When a new call is incoming during call communication, click MFB button to end the current call and answer the new call (some phones need to click MFB again). 2) Long press MFB about one second to keep the current call (Call A), and answer Call B. Long press MFB about one second again to switch to Call A. Repeat this action to switch Call A/B. 3) Click MFB once during call communication to end the current call and recover the other call.

22

Tips

- 1.To extend the service life of the battery, you are advised to charge the earphone at least once a month.
- 2.Please use the charger provided by company to charge the earphone. Use of other low-quality chargers may bring about dangers.
- 3.Adjust the volume to an appropriate degree when using the earphone.
- 4.DO NOT wear the earphone when sleeping; otherwise, the earphone may be damaged or cause injuries to you.
- 5.Keep the earphone away from kids. Small components of the earphone may cause suffocation or other injuries to kids.

27

the earphone. 3. Find the Bluetooth earphone, pairing it to finish the connected.

Basic Operations

Power-on pairing: Long press MFB about 3 seconds, the red and blue indicators blink at the same time for three times, the voice prompt "Power On, Pairing" is played on the earphone, then auto enter into a paring mode with red & blue light flash alternately. The earphone will be automatically powered off if pairing is not completed within 150 seconds.

Connecting: After successful paring with the cell phone, the voice prompt "Pairing Success, Sound Connected" is

18

Charger and Battery

Before using any charger to charge this earphone, check whether the specifications of the charger meet requirements. The recommended output voltage of the charger is DC5V+/-0.25V, and the recommended output current is 100 mA to 500 mA. An over-high charging voltage may damage the earphone.

Warning: Use the recommended charger whenever possible. Use of other types of chargers may violate the warranty terms of the equipment and results in danger. If the charging cable is delivered with the earphone, connect the cable to a CCC-certified charger or computer to charge the earphone.

23